

# PLUG & PLAY—Switch





CASAMBI Smart adapter for lights and electrical appliances

CASAMBI



# AIMOTION

## Features

-  Automatic switching on and off
-  Switch to sun time
-  Create scenes
-  High switching capacity - up to 3680W

## Switch - smart adapter for lights and electrical appliances

### Description

The switch enables the switching of conventional bulbs and other electrical devices. The product is Casambi Ready and therefore compatible with all AIMOTION systems and Casambi powered lights.

### Safety instructions:

When working on the connected device, please remove it from the socket of the switch. Disconnect appliances that generate heat from the mains, i.e. from the switch, after use to prevent accidental power-up. Very large capacitive and inductive loads can in unfavourable cases lead to the destruction of the device or reduce the number of switching cycles. Do not use the switch with medical devices. To connect to a B16A circuit breaker.




### Declaration of Conformity:

Hereby AIMOTION GmbH declares that the product Plug & Play Switch is in compliance with ROHS Directive 2011/65/EC, RED 2014/53/EU and EC No. 1907/2006 REACH.

  
Chief Technology Officer (CTO)  
Timo Lühmann  
23.03.2021

The detailed declaration of conformity can be found at <https://www.aimotion-smartliving.de/en/support-en/download/> in the product category Switching Actuators.

## Technical data

<b>Input</b>		<b>Operating conditions</b>	
Voltage range:	220-240 VAC	Operating temperature:	0...50 °C
Frequency:	50 Hz	Storage temperature:	-25...+65 °C
		Max. relative humidity:	0...80%, non-cond.
<b>Mains Output</b>		<b>Mechanical data</b>	
Voltage range:	220-240 VAC	Color:	Black or white
Frequency:	50 Hz	Dimensions (without plug):	85 x 55 x 45 mm
Max. switchable current:	16 A	Weight:	180g
Max. switchable power:	3680 W	Protection class:	I
		Degree of protection:	IP20 (indoor use only)
<b>Radio transceiver</b>		  	
Operating frequencies:	2,4...2,483 Ghz		
Max. output power:	+4 dBm		

### Disposal instructions

In line with EU Directive 2002/96/EC for waste electrical and electronic equipment (WEEE), this electrical product must not be disposed of as unsorted municipal waste.

Please dispose of this product by returning it to the point of sale or to your local municipal collection point for recycling.

The products of the PLUG & PLAY series by AIMOTION are available in black and white.



iPhone 4S or later  
iPad 3 (2012, A14xx) or later  
iPod Touch 6th gen or later



Android 4.4 KitKat devices or later  
Produced with full Bluetooth 4.0 support

